SIEMENS

Data sheet



SIMATIC S7-300, Counter module FM 350-2, 8 channels, 20 kHz, 24 V encoder for $counting, frequency\ measurement,\ speed\ measurement,\ period\ duration$ measurement, dosing incl. configuration package and electronic documentation on

Figure similar

Supply voltage	
Auxiliary voltage 1L+, load voltage 2L+	
Rated value (DC)	24 V
 permissible range, lower limit (DC) 	20.4 V
 permissible range, upper limit (DC) 	28.8 V
Input current	
from load voltage L+ (without load), max.	150 mA
from backplane bus 5 V DC, max.	100 mA
Encoder supply	
NAMUR encoder supply	
• 8.2 V	Yes
Short-circuit protection	Yes
 Output current, max. 	200 mA
Power loss	
Power loss, typ.	10 W
Digital inputs	
Number of digital inputs	8
Number of NAMUR inputs	8
Functions	1 each for gate start/ gate stop
Input voltage	
● for signal "0"	-3 to +5V
● for signal "1"	11 to 30.2 V
Input current	
for signal "0", max. (permissible quiescent current)	2 mA
● for signal "1", typ.	9 mA
for NAMUR encoders	
— for signal "0", max.	1.2 mA
— for signal "1", min.	2.1 mA
Input delay (for rated value of input voltage)	
Input frequency, max.	20 kHz
for standard inputs	
— at "0" to "1", max.	50 µs
for NAMUR inputs	
— at "0" to "1", max.	50 µs
Cable length	
shielded, max.	100 m
Digital outputs	
Number of digital outputs	8
Short-circuit protection	Yes

L+ (-40 V)
L+ (-0.8 V)
0.5 A
0.5 mA
300 μs
500 Hz
0.5 Hz
4 A
2 A
2 A
600 m
100 m
Yes
Yes
Yes
Yes; to DIN 19 234
Yes
165
Yes; Diagnostic information readable
res, Diagnostic information readable
Yes; Parameterizable
1 65, 1 didiliciciizable
Voc: Parameterizable
Yes; Parameterizable
Yes; Parameterizable Yes
Yes
Yes 8; 32 bit or ±31 bit
Yes 8; 32 bit or ±31 bit -3 to +5V
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding Yes; and shielding
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding Yes; and shielding Yes; and shielding
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding Yes; and shielding
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding Yes; and shielding Yes; and shielding
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding Yes; and shielding Yes; and shielding
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding Yes; and shielding Yes; and shielding
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding Yes; and shielding 1x 40-pin 80 mm
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding Yes; and shielding 1x 40-pin 80 mm 125 mm
Yes 8; 32 bit or ±31 bit -3 to +5V 11 to 30.2 V 9 mA 20 kHz; Incremental encoder: 10 kHz Yes; and shielding Yes; and shielding 1x 40-pin 80 mm 125 mm



last modified:

8/16/2023